
Flex Sensor





Nominal Resistance Flex 0 Degrees: 10 K

Flex 90 Degrees 30-40 K

Proportional increase in resistance as sensor is bent or flexed. Maximum resistance 30K - 40K ohms.

Applications:

Virtual Reality Data Gloves Robotic Sensor Bio-Metric Sensor Physics & Engineering Sensor

Nominal Resistance 10,000 ohms (10K) Range 10K to 40K ohms FLX-01 \$ 10.00

Images Company 39 Seneca Loop Staten Island NY 10314 (718) 698-8305 Voice (718) 982-6145 Fax